3. Electrical Parts List

*S.N.A. : Service Not Available

Location no.	Code no.	Description & Specifiation	Remarks
		****** MM-B9 Parts List ******	
JCW1-1	3809-001223	CABLE-FLAT;30V,80C,50mm,13P,1.25mm,UL289	
TCW1-1	3809-001223	CABLE-FLAT;30V,80C,50mm,13P,1.25mm,UL289	
	3809-001280	CABLE-FLAT;30V,80C,250MM,17P,1.25MM,UL28	
MAIN-FR	3809-001291	CABLE-FLAT;30V,80C,150MM,21P,1.25MM,UL28	
RT1	AH26-00161A	TRANS POWER;-,MM-B9,-,5P/10P,230V,-,-,-,	
	AH31-00029A	MOTOR FAN;C161NK10B0110,RDM6015S,0.15A,-	
	AH38-10001A	FM-WIRE;1007#22,1500MM	
	AH39-00257G	POWER CORD;MAX980,-,CP2,250V,2.5A,1830MM	
	AH40-00024D	TUNER;KST-MN114LS1-55,MM-ZB9,-,-,-,-	
	AH42-20001P	LOOP-ANT;TT,1000MM,18.5UH	
	AH59-00134D	REMOCON-ASSY;MM-B9,SAMSUNG,-,-,27KEY,-,-	
	AH59-00138D	**DECK-MECHA ASSY;-,CD,-,-,-,-,-,-,-**	
	3409-001078	LEAF SWITCH;MSW-1731-CVCA	
	3809-001289	CABLE-FLAT;30V,80C,90MM,16P,1MM,UL20696	
	AH31-00030A	MOTOR DC;-,RF-300CH,86MA,-,-,1~6V,1410?	
	AH59-01006A	DECK;CMS-P73SG6,MM-Z100UH,-,19.4MM,	
	AH30-00007A	PICK UP;SOH-AA,D73SG6(U)	
	AH92-00921B	**ASSY PCB-CD(ONLY);MM-B100MH,G3HI-1CD/CDP**	
IC401	1003-001162	IC-MOTOR DRIVER;KA3082,SIP,10PIN,25MIL,D	
X201	2802-000211	RESONATOR-CERAMIC;16.93MHz,0.5%,TP,10.0x	
CW105	3708-000189	CONNECTOR-FPC/FFC/PIC;17P,1.25mm,ANGLE,S	
CW101	3708-001388	CONNECTOR-FPC/FFC/PIC;16P,1MM,ANGLE,SN	
	3711-000906	CONNECTOR-HEADER;BOX,3P,1R,2mm,ANGLE,SN	
CW103	3711-000988	CONNECTOR-HEADER;BOX,5P,1R,2mm,ANGLE,SN	
CW106	AH39-00060A	LEAD CONNECTOR-ASSY;-,51015-08,51004-08,	
ZD301	0403-000344	DIODE-ZENER;UZ3.9B,3.9V,3.7-4.1V,500mW,D	
ZD401	0403-000357	DIODE-ZENER;UZ5.6BM,5.6V,5.4-5.8V,500mW,	
Q302	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,	
Q101	0501-000314	TR-SMALL SIGNAL;KSA812,PNP,150mW,SOT-23,	
Q301	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,	
IC201	0904-001524	IC-DSP;5L9290,-,QFP,48P,472MIL,16.934	
IC301	1003-000179	IC-MOTOR DRIVER;KA9258D,SOP,28P,-,SINGLE	
IC101	1204-001799	IC-ASP;KB9226,LQFP,48P,393MIL,PLASTIC	
R502L	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R805	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R804	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R213	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R212	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R211	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R205	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
0R806	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R803	2001-000515	R-CARBON;220ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R206	2001-000515	R-CARBON;220ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R302	2001-001006	R-CARBON;82ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R114	2007-000001	R-CHIP;68KOHM,5%,1/10W,DA,TP,2012	
J46	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J44	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J43	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J42	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J35	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J36	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J41	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J3	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J25	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J24	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J23	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J22	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J4	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J9	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J8	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J7	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J6	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J5	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J15	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J13	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J12	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J10	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J1	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J16	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J20	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J2	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J19	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J18	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J17	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
R501R	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
R501L	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
R502R	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
R133	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R132	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
MR3	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
MR2	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R108	2007-000308	R-CHIP;10OHM,5%,1/10W,DA,TP,2012	

Location no.	Code no.	Description & Specifiation	Remarks
R124	2007-000338	R-CHIP;120KOHM,5%,1/10W,DA,TP,2012	
R125	2007-000338	R-CHIP;120KOHM,5%,1/10W,DA,TP,2012	
R117	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
R121	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
R113	2007-000444	R-CHIP;180KOHM,5%,1/10W,DA,TP,2012	
R110	2007-000457	R-CHIP;18KOHM,5%,1/10W,DA,TP,2012	
R402	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R401	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R209	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R202	2007-000477	R-CHIP;1MOHM,5%,1/10W,DA,TP,2012	
R118	2007-000477	R-CHIP;1MOHM,5%,1/10W,DA,TP,2012	
R303	2007-000502	R-CHIP;2.2OHM,5%,1/10W,DA,TP,2012	
R116	2007-000546	R-CHIP;20KOHM,5%,1/10W,DA,TP,2012	
R210	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
R208	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
R207	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
R204	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
R128	2007-000653	R-CHIP;27KOHM,5%,1/10W,DA,TP,2012	
R129	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
R123	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
R126	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
R120	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
R104	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
R103	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
R102	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
R101	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
R115	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
R112	2007-001195	R-CHIP;820KOHM,5%,1/10W,DA,TP,2012	
R127	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012	
R119	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012	
R106	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012	
R105	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012	
R107	2007-001216	R-CHIP;82OHM,5%,1/10W,DA,TP,2012	
R301	2008-000140	R-FUSIBLE;2.2ohm,5%,1/2W,AA,TP,3.5x9.4mm	
C205	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C211	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C213	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C216	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C218	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C220	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C402	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C204	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C115	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C116	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C118	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C124	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C132	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C130	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C129	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C401	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,2012,-,T	
C207	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,2012,-,T	
C134	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,2012,-,T	
C103	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,2012,-,T	
C105	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,2012,-,T	
C121	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,2012,-,T	
C124	2203-000347	C-CERAMIC,CHIP;150nF,10%,50V,NPO,2012,-,	
JW9<->JW10	2203-000477	C-CERAMIC,CHIP;1uF,+80-20%,16V,Y5V,2012,	
C126	2203-000495	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,2012,-,	
C127	2203-000595	C-CERAMIC,CHIP;220PF,5%,50V,NPO,TP,2012	
C119	2203-000802	C-CERAMIC,CHIP;33NF,10%,50V,X7R,2012,TP	
C128	2203-000802	C-CERAMIC,CHIP;33NF,10%,50V,X7R,2012,TP	
C125	2203-000840	C-CERAMIC,CHIP;390pF,5%,50V,NPO,2012,-,T	
C111	2203-000892	C-CERAMIC,CHIP;4.7NF,10%,50V,X7R,TP,2012	
C112	2203-000892	C-CERAMIC,CHIP;4.7NF,10%,50V,X7R,TP,2012	
C135	2203-000919	C-CERAMIC,CHIP;470nF,+80-20%,16V,Y5V,201	
C120	2203-000919	C-CERAMIC,CHIP;470nF,+80-20%,16V,Y5V,201	
C109	2203-001026	C-CERAMIC,CHIP;4pF,5%,16V,NPO,2012,-,TP	
C124A	2203-001063	C-CERAMIC,CHIP;56nF,10%,16V,X7R,1608,-,T	
C122	2203-001137	C-CERAMIC,CHIP;68nF,+80-20%,50V,Y5V,2012	
C106	2203-001137	C-CERAMIC,CHIP;68nF,+80-20%,50V,Y5V,2012	
C203	2203-001223	C-CERAMIC,CHIP;820pF,10%,50V,X7R,2012,2.	
C502R	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
C502L	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
C117	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
C102	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
C104	2203-001551	C-CERAMIC,CHIP;1.5nF,10%,50V,X7R,TP,2012	
C202	2203-001619	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,201	
C201	2203-001619	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,201	
C123	2401-000407	C-AL;10uF,20%,16V,GP,3.5*5,2.5MM,TP	
C303	2401-001102	C-AL;330uF,20%,16V,GP,8*11.5,5MM,TP	
C301	2401-001102	C-AL;330uF,20%,16V,GP,8*11.5,5MM,TP	
C114	2401-001238	C-AL;4.7uF,20%,25V,GP,BK,3x5,1mm	
C501L	2401-001238	C-AL;4.7uF,20%,25V,GP,BK,3x5,1mm	
C501R	2401-001238	C-AL;4.7uF,20%,25V,GP,BK,3x5,1mm	
C302	2401-001895	C-AL;100uF,20%,16V,GP,TP,6.3x11,2.5	
C304	2401-001934	C-AL;220uF,20%,6.3V,GP,6.3x7,2.5MM	
C217	2401-001934	C-AL;220uF,20%,6.3V,GP,6.3x7,2.5MM	
C215	2401-001934	C-AL;220uF,20%,6.3V,GP,6.3x7,2.5MM	
C210	2401-001934	C-AL;220uF,20%,6.3V,GP,6.3x7,2.5MM	

Location no.	Code no.	Description & Specifiation	Remarks
C131	2401-001934	C-AL;220uF,20%,6.3V,GP,6.3x7,2.5MM	
C108	2401-001934	C-AL;220uF,20%,6.3V,GP,6.3x7,2.5MM	
C107	2401-001934	C-AL;220uF,20%,6.3V,GP,6.3x7,2.5MM	
C101	2401-001934	C-AL;220uF,20%,6.3V,GP,6.3x7,2.5MM	
DL1	2701-000111	INDUCTOR-AXIAL;100uH,10%,2.5x3.4mm	
	AH97-00863A	**ASSY CDP DECK-G3HI-1CD/MP3;-,-,G3HI-1CD/**	
	3302-000159	MAGNET-FERRITE;AC,-,3500-3800G,6P FERRIT	
	3409-001119	SWITCH-DETECTOR;5V DC,1.0A,DPST,30gf,-	
	AH39-00104A	LEAD CONNECTOR-ASSY;-,35023,51004,5P,200	
	AH59-01038B	**SPEAKER SYSTEM;PSB9E,-,-,-,-,-,-,ELS,-**	
	AH92-01330B	**ASSY PCB-KOR,TAP;MM-B9,SUM**	
ULED2	0601-001432	LED;SLP340BL10F,470NM,3MM	
ULED1	0601-001432	LED;SLP340BL10F,470NM,3MM	
ULED3	0601-001436	LED;SELU1E10CXM BLUE5MM,470NM	
ULED4	0601-001436	LED;SELU1E10CXM BLUE5MM,470NM	
OJ1	0603-001069	OPTIC TRANSMITTER;5V,8Mb/s,-,-17dBm,660n	
XD1(SIDE)	2202-000797	C-CERAMIC,MLC-AXIAL;10NF,30%,16V,Y5S,TP,	
OL1	2901-001139	FILTER-EMI ON BOARD;50V,.5A,-,390PF,7*2	
UVR1	3406-001047	SWITCH-ROTARY;RE012104PVB25FINB1-2-24E	
UVR3	3406-001050	SWITCH-ROTARY;RE012103PVB25FINB1-2-24PCE	
UVR2	3406-001050	SWITCH-ROTARY;RE012103PVB25FINB1-2-24PCE	
UCW2	3711-000596	CONNECTOR-HEADER;BOX,10P,1R,2mm,STRAIGHT	
UCW3	3711-000968	CONNECTOR-HEADER;BOX,4P,1R,2mm,STRAIGHT,	
HCW2	3711-001136	CONNECTOR-HEADER;BOX,8P,1R,2mm,ANGLE,SN	
ACW2	3711-003107	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
MJ1	3722-001588	JACK-PHONE;7P,3.6PI,AG,BLK,-	
HJ1	3722-001588	JACK-PHONE;7P,3.6PI,AG,BLK,-	
LCD1	AH07-00064A	LCD;-,MM-B9,8,56*40,-,-,-,-,5V,-,-	
OIC1	AH14-10004R	IC;M74HCU04,SOP,TAPE,14P	
	AH39-00096B	LEAD CONNECTOR ASSY;#1007,28,AWG28,3P,30	
UCW6	AH39-00393A	CONNECT WIRE;-,-,-,10P;-,-,-,5295,51004,	
UCW5	AH39-00398A	CONNECT WIRE;-,-,-,4P,-,-,-,35023,51004,	
ACW3	AH39-00400A	CONNECT WIRE;-,-,-,3P,-,-,-,5264,51088,-	
AMONO WIRE	AH39-50001K	LEAD-FASTEN;RING,1007#24,140MM,BLK	
RMC1	AH59-60001J	MODULE REMOCON;GP1U271R,38KHZ,-,MESH,-,	
	AH61-00898A	HOLDER-LCD;MM-B9,ABS 94HB,-,-,-,WHT,-	
	AH63-00364A	FILTER-LCD;MM-B9,KIMO,120,-,-,-,-	
	AH63-00384A	SHIELD-SPK,8;HT-DL100,SPTE 0.3T,-,-,-,-,	
	AH67-00141A	LENS-LCD;MM-B9,PMMA,CLEAR,-,-,-,-	
XD4	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
XD3	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
XD2	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
XD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
UD51	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
UD52	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
UJW14	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
UQ9	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-	
UQ8	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-	
UQ5	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-	
UQ3	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-	
UQ10	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-	
UR80	2001-000027	R-CARBON;100ohm,5%,1/4W,AA,TP,2.4x6.4mm	
UR79	2001-000027	R-CARBON;100ohm,5%,1/4W,AA,TP,2.4x6.4mm	
HR2	2001-000110	R-CARBON;10ohm,5%,1/4W,AA,TP,2.4x6.4mm	
HR1	2001-000110	R-CARBON;10ohm,5%,1/4W,AA,TP,2.4x6.4mm	
UR69	2001-000221	R-CARBON;1.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR76	2001-000221	R-CARBON;1.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR75	2001-000241	R-CARBON;1.5Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR68	2001-000241	R-CARBON;1.5Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR92	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR91	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR90	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR88	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR86	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR84	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR77	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR70	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR66	2001-000472	R-CARBON;2.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR73	2001-000472	R-CARBON;2.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR72	2001-000613	R-CARBON;3.9Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR65	2001-000613	R-CARBON;3.9Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR51	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR64	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR78	2001-000995	R-CARBON;820ohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR71	2001-000995	R-CARBON;820ohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR59	2001-001107	R-CARBON(S);220ohm,5%,1/2W,AA,TP,2.4x6.4	
UR58	2001-001107	R-CARBON(S);220ohm,5%,1/2W,AA,TP,2.4x6.4	
UR57	2001-001107	R-CARBON(S);220ohm,5%,1/2W,AA,TP,2.4x6.4	
OC2	2201-000381	C-CERAMIC,DISC;22nF,+80%,50V,-,,8x4mm,-	
OC1	2201-000487	C-CERAMIC,DISC;33pF,5%,50V,SL,TP,5x3,5m	
HC11	2202-000850	C-CERAMIC,MLC-AXIAL;2.2NF,20%,16V,Y5R	
HC12	2202-000850	C-CERAMIC,MLC-AXIAL;2.2NF,20%,16V,Y5R	
UC52	2202-000854	C-CERAMIC,MLC-AXIAL;47nF,30%,50V,Y5R,TP,	
OC3	2401-000240	C-AL;100uF,20%,10V,GP,5*11mm,5mm,TP	
HL1	2701-000298	INDUCTOR-AXIAL;470uH,10%,4.2x9.8mm	
HL2	2701-000298	INDUCTOR-AXIAL;470uH,10%,4.2x9.8mm	
HL3	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,	
USW2	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW3	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW4	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW5	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW6	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW7	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW8	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW9	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW17	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW1	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW10	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW11	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW12	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW16	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW15	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW14	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW13	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
	AH92-01331A	**ASSY PCB-TAPE;MM-B9,TAPE**	
JIC1	1201-001819	IC-PREAMP;-,-,44P,-,-,-,PLASTIC,18V,625M	
JCON2	3708-000193	CONNECTOR-FPC/FFC/PIC;17P,1.25mm,STRAIGH	
JCON3	3708-001029	CONNECTOR-FPC/FFC/PIC;9P,1.25mm,STRAIGHT	
JL1L	AH26-10002W	COIL-TRAP;BIAS-TRAP105K,BIAS-TRAP,32DB,9	
JL1R	AH26-10002W	COIL-TRAP;BIAS-TRAP105K,BIAS-TRAP,32DB,9	
JT1	AH26-10003C	COIL-TRAP;PCHNS-5371EQJ,BIAS-TRAP,-,-,85	
JCON1	AH39-00360A	LEAD CONNECTOR ASSY;MM-Z100,1533#28,-,6P	
JD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
JD2	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
JZD1	0403-000354	DIODE-ZENER;UZ5.1B,5.1V,4.8-5.4V,500mW,D	
JQ5R	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,	
JQ5L	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,	
JQ4R	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,	
JQ4L	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,	
JQ9	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
JQ8	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
JQ7	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,	
JQ13	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,	
JQ12	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,	
JQ11	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-	
JQ10	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-	
JQ3	0504-001003	TR-DIGITAL;KSR2003TA,300mW,22K-22Kohm	
JR28R	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR28L	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR19	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR18	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR21	2001-000034	R-CARBON;220ohm,5%,1/4W,AA,TP,2.4x6.4mm	
JR26R	2001-000241	R-CARBON;1.5Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR26L	2001-000241	R-CARBON;1.5Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR16	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR27R	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR27L	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR33	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR40	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR32R	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR32L	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR2	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR1	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR7R	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR7L	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR24R	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR24L	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR14	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR35	2001-000435	R-CARBON;1Mohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR9	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR5R	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR5L	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR31R	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR31L	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR30R	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR30L	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR13	2001-000456	R-CARBON;2.2ohm,5%,1/4W,AA,TP,2.4x6.4mm	
JR3	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR34	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR8	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR11R	2001-000563	R-CARBON;27Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR11L	2001-000563	R-CARBON;27Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR10	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR20	2001-000660	R-CARBON;33Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR17	2001-000660	R-CARBON;33Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR4R	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR4L	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR41	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR39	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR38	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR37	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR36	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR29R	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR29L	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR25R	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR25L	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR12	2001-001153	R-CARBON(S);47ohm,5%,1/2W,AA,TP,2.4x6.4m	
JR23	2001-001178	R-CARBON(S);680ohm,5%,1/2W,AA,TP,2.4x6.4	
JR22	2001-001178	R-CARBON(S);680ohm,5%,1/2W,AA,TP,2.4x6.4	
JC19R	2201-000163	C-CERAMIC,DISC;10nF,+80-20%,50V,Y5V,6.5*	
JC19L	2201-000163	C-CERAMIC,DISC;10nF,+80-20%,50V,Y5V,6.5*	
JC17R	2201-000163	C-CERAMIC,DISC;10nF,+80-20%,50V,Y5V,6.5*	
JC17L	2201-000163	C-CERAMIC,DISC;10nF,+80-20%,50V,Y5V,6.5*	
JC4R	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	

Location no.	Code no.	Description & Specifiation	Remarks
JC4L	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
JC15L	2201-000783	C-CERAMIC,DISC;100nF,+80-20%,50V,Y5V,TP,	
JC15R	2201-000783	C-CERAMIC,DISC;100nF,+80-20%,50V,Y5V,TP,	
JC11R	2202-000847	C-CERAMIC,MLC-AXIAL;1,8nF,30%,50V,Y5S,TP	
JC11L	2202-000847	C-CERAMIC,MLC-AXIAL;1,8nF,30%,50V,Y5S,TP	
JC22L	2202-000850	C-CERAMIC,MLC-AXIAL;2.2NF,20%,16V,Y5R	
JC22R	2202-000850	C-CERAMIC,MLC-AXIAL;2.2NF,20%,16V,Y5R	
JC13R	2301-000379	C-FILM,PEF;10nF,10%,50V,6x12x3.5,TP	
JC13L	2301-000379	C-FILM,PEF;10nF,10%,50V,6x12x3.5,TP	
JC8	2301-000390	C-FILM,PEF;15nF,10%,50V,7x12x3.5,TP	
JC6	2301-000404	C-FILM,PEF;2.2nF,10%,50V,5.5x12x3,TP	
JC5	2301-000407	C-FILM,PEF;2.7nF,10%,50V,5.5x12x3,TP	
JC27	2401-000240	C-AL;100uF,20%,10V,GP,5*11mm,5mm,TP	
JC24	2401-000303	C-AL;100uF,20%,25V,GP,6.3*11,5MM,TP	
JC30	2401-001912	C-AL;1uF,20%,50V,GP,BK,5x11mm,2mm	
JC18R	2401-001912	C-AL;1uF,20%,50V,GP,BK,5x11mm,2mm	
JC18L	2401-001912	C-AL;1uF,20%,50V,GP,BK,5x11mm,2mm	
JC10	2401-001912	C-AL;1uF,20%,50V,GP,BK,5x11mm,2mm	
JC3	2401-001954	C-AL;4.7UF,20%,50V,GP,5*11,5MM,TP	
JC23	2401-001954	C-AL;4.7UF,20%,50V,GP,5*11,5MM,TP	
JC16R	2401-001954	C-AL;4.7UF,20%,50V,GP,5*11,5MM,TP	
JC16L	2401-001954	C-AL;4.7UF,20%,50V,GP,5*11,5MM,TP	
JC9R	2401-001975	C-AL;47uF,20%,16V,GP,5*11,5mm,TP	
JC9L	2401-001975	C-AL;47uF,20%,16V,GP,5*11,5mm,TP	
JC7	2401-001975	C-AL;47uF,20%,16V,GP,5*11,5mm,TP	
JC20R	2401-002180	C-AL;2.2uF,20%,50V,GP,5*11,5mm,TP	
JC20L	2401-002180	C-AL;2.2uF,20%,50V,GP,5*11,5mm,TP	
JL2	2701-000298	INDUCTOR-AXIAL;470uH,10%,4.2x9.8mm	
	AH92-01332B	**ASSY PCB-MAIN/POWER;MM-B9,MAIN/POWER,QH**	
RD19	0402-000157	DIODE-RECTIFIER;1N5402,200V,3A,DO-201AD,	
RD18	0402-000157	DIODE-RECTIFIER;1N5402,200V,3A,DO-201AD,	
RD17	0402-000157	DIODE-RECTIFIER;1N5402,200V,3A,DO-201AD,	
RD14	0402-000157	DIODE-RECTIFIER;1N5402,200V,3A,DO-201AD,	
RD15	0402-000157	DIODE-RECTIFIER;1N5402,200V,3A,DO-201AD,	
RD16	0402-000157	DIODE-RECTIFIER;1N5402,200V,3A,DO-201AD,	
AQ15	0502-001126	TR-POWER;2SD2390,NPN,100W,SC-62,BK,6500	
RQ4	0502-001197	TR-POWER;KSD1406,NPN,25000MW,TO-220F	
RQ2	0502-001197	TR-POWER;KSD1406,NPN,25000MW,TO-220F	
AIC1	1201-001818	IC-POWER AMP;-,-,25P,29MIL,QUAD,26DB,PLA	
AIC4	1203-000110	IC-NEGA.FIXED REG.;7912,TO-220,3P;-,PLAS	
AIC3	1203-000242	IC-POSI.FIXED REG.;7812,TO-220,3P;-,PLAS	
RIC1	1203-000276	IC-POSI.FIXED REG.;7805,TO-220,3P;-,PLAS	
DIC7	1204-001454	IC-VOLUME CONTROL;TDA7449L,DIP,20P,300MI	
AR50	2003-000616	R-METAL OXIDE(S);27ohm,5%,2W,AA,TP,4x12m	
AR52	2003-000616	R-METAL OXIDE(S);27ohm,5%,2W,AA,TP,4x12m	
	2003-000807	R-METAL OXIDE(S);82ohm,5%,2W,AA,TP,4x12m	
RC1	2201-000546	C-CERAMIC,DISC;4.7nF,20%,400V,Y5U,16.0*7	
RC2	2201-000546	C-CERAMIC,DISC;4.7nF,20%,400V,Y5U,16.0*7	
RC8	2201-000795	C-CERAMIC,DISC;10nF,10%,400V,Y5P,TP,15x1	
RC4	2201-000795	C-CERAMIC,DISC;10nF,10%,400V,Y5P,TP,15x1	
RC13	2201-000795	C-CERAMIC,DISC;10nF,10%,400V,Y5P,TP,15x1	
	2202-000854	C-CERAMIC,MLC-AXIAL;47nF,30%,50V,Y5R,TP,	
	2202-000854	C-CERAMIC,MLC-AXIAL;47nF,30%,50V,Y5R,TP,	
RC9	2401-001052	C-AL;3300uF,20%,25V,GP,-,16x31.5,7.	
RC5	2401-001052	C-AL;3300uF,20%,25V,GP,-,16x31.5,7.	
RC26	2401-001052	C-AL;3300uF,20%,25V,GP,-,16x31.5,7.	
RC25	2401-001413	C-AL;470UF,20%,35V,GP,10X20,5MM	
HR11<->GND	2401-001465	C-AL;47uF,20%,10V,GP,5*11,5mm,TP	
AC44	2401-001633	C-AL;6800uF,20%,25V,GP,BK,18x35.5,7	
RC31	2401-001886	C-AL;1000uF,20%,35V,GP,16x25mm,5mm,	
RC30	2401-001886	C-AL;1000uF,20%,35V,GP,16x25mm,5mm,	
AC47	2401-001886	C-AL;1000uF,20%,35V,GP,16x25mm,5mm,	
AC46	2401-001886	C-AL;1000uF,20%,35V,GP,16x25mm,5mm,	
UX1	2801-001394	CRYSTAL-UNIT;32.768KHz,20ppm,28-AAY,12.5	
UX2	2802-000181	RESONATOR-CERAMIC;6MHZ,0.3%,BK,9.0X4.0X7	
RRL1	3501-001159	RELAY-MINIATURE;SDT-SS-112DM	
RF1	3601-000162	FUSE-CARTRIDGE;250V,1.25A,TIME-LAG,GLASS	
RF6	3601-000170	FUSE-CARTRIDGE;250V,1.6A,TIME-LAG,GLASS,	
RF7	3601-000248	FUSE-CARTRIDGE;250V,2A,TIME-LAG,GLASS,5x	
RF3	3601-000319	FUSE;80MA(15.5MM)	
JCW1	3708-000193	CONNECTOR-FPC/FFC/PIC;17P,1.25mm,STRAIGH	
CCW3	3708-000193	CONNECTOR-FPC/FFC/PIC;17P,1.25mm,STRAIGH	
UCW1	3708-000219	CONNECTOR-FPC/FFC/PIC;21P,1.25mm,STRAIGH	
TCW1	3708-001094	CONNECTOR-FPC/FFC/PIC;13P,1.25mm,STRAIGH	
RJ1	3711-000190	CONNECTOR-HEADER;1WALL,2P,1R,7.92mm,STRA	
RCW2	3711-000658	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,STRAIG	
FA4	3711-000820	CONNECTOR-HEADER;BOX,2P,1R,2.5mm,STRAIGH	
RCW1	3711-001018	CONNECTOR-HEADER;BOX,5P,1R,2mm,STRAIGHT,	
CCW2	3711-001137	CONNECTOR-HEADER;BOX,8P,1R,2mm,STRAIGHT,	
AJ1	3716-001132	TERMINAL-BLOCK;SOLDER,4P,-,-,-	
AJ2	3716-001179	TERMINAL-BLOCK;SOLDER,4P,6.3MM,60V,7A	
AJ4	3722-000377	JACK-RCA;4P/2C,3.5mm,#16~22,SN	
RT2	AH26-00161C	TRANS POWER;-,MM-B9,-,-,230V,8.7V,15.5V,	
RL2	AH27-10001F	COIL-CHOKE;27uH,K,Q30,-,-,DR(6.5*7.5),-,	
RL1	AH27-10001F	COIL-CHOKE;27uH,K,Q30,-,-,DR(6.5*7.5),-,	
JW114	AH27-90001A	COIL-SPRING;,2.2UH,-,-,SPRING	
JW117	AH27-90001A	COIL-SPRING;,2.2UH,-,-,SPRING	
HCW1	AH39-00103A	LEAD CONNECTOR-ASS;-,5295,51004,8P,210MM	
MONO WIRE	AH39-00134A	LEAD-FASTEN;RING,1007#24,60MM,BLK	
PCW1	AH39-00399A	CONNECT WIRE;-,-,-,12P,-,-,-,5264,51088,	
CCW1	AH39-20006G	LEAD-CONNECTOR ASS'Y;51004,5295,5P,300MM	
B	AH39-50001K	LEAD-FASTEN;RING,1007#24,140MM,BLK	

Location no.	Code no.	Description & Specifiation	Remarks
	AH62-00067A	INSULATION-RUBBER;MM-B9,TC-20CG,-,-,-,PI	
UD9	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
UD8	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
UD7	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
UD6	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
AD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
RD36	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
UD10	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
UD12	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
RD40	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD4	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD39	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD37	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD35	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD8	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD7	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD6	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD5	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD41	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD13	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD12	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD11	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD10	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD1	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD34	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD33	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD32	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD3	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD2	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RZD8	0403-000354	DIODE-ZENER;UZ5.1B,5.1V,4.8-5.4V,500mW,D	
RZD1	0403-000379	DIODE-ZENER;UZP12B,12V,11.4-12.6V,1W,DO-	
AZD3	0403-000379	DIODE-ZENER;UZP12B,12V,11.4-12.6V,1W,DO-	
AZD1	0403-000379	DIODE-ZENER;UZP12B,12V,11.4-12.6V,1W,DO-	
AZD4	0403-000393	DIODE-ZENER;UZP5.1B,5.1V,4.8-5.4V,1W,DO-	
AZD2	0403-000393	DIODE-ZENER;UZP5.1B,5.1V,4.8-5.4V,1W,DO-	
RZD3	0403-000399	DIODE-ZENER;UZP9.1B,8.5-9.6V,1W,DO-41,TP	
FZD2	0403-000399	DIODE-ZENER;UZP9.1B,8.5-9.6V,1W,DO-41,TP	
FZD1	0403-000399	DIODE-ZENER;UZP9.1B,8.5-9.6V,1W,DO-41,TP	
RQ16	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,	
AQ13	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,	
RQ5	0501-000294	TR-SMALL SIGNAL;KSA708-Y,PNP,800mW,TO-92	
UQ1	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
RQ6	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
HQ2	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
HQ1	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
FQ2	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9	
FQ1	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9	
HQ3	0504-001003	TR-DIGITAL;KSR2003TA,300mW,22K-22Kohm	
FQ3	0504-001003	TR-DIGITAL;KSR2003TA,300mW,22K-22Kohm	
HIC1	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/m	
FIC5	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/m	
FIC3	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/m	
FIC2	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/m	
DIC9	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/m	
FIC1	1204-001776	IC-SOUND PROCESSOR;TDA7442D,SOP,28P,295M	
FR31	2001-000016	R-CARBON(S);10HM,5%,1/2W,AA,TP,2.4*6.4MM	
RR10	2001-000027	R-CARBON;100ohm,5%,1/4W,AA,TP,2.4x6.4mm	
RR11	2001-000027	R-CARBON;100ohm,5%,1/4W,AA,TP,2.4x6.4mm	
FR13L	2001-000258	R-CARBON;1.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR24R	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR2	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR1	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR54	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR53	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR34	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
RR13	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR26R	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR26L	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
AR36	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR61	2001-000331	R-CARBON;12Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR6R	2001-000411	R-CARBON;18Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR6L	2001-000411	R-CARBON;18Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR14	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR15	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR17	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR8	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR9	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR13	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
RR35	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
RR39	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR10	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR11	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR12	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR25R	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR25L	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
AR13R	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
AR13L	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
RR9	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR3R	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR3L	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
HR4	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
HR11	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR1R	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	

Location no.	Code no.	Description & Specifiation	Remarks
FR1L	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
RR38	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
RR37	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR5R	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
AR19	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
AR12L	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
AR12R	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
RR36	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
AR51	2001-001077	R-CARBON(S);150ohm,5%,1/2W,AA,TP,2.4x6.4	
RR4	2001-001107	R-CARBON(S);220ohm,5%,1/2W,AA,TP,2.4x6.4	
RR101	2001-001195	R-CARBON(S);82ohm,5%,1/2W,AA,TP,2.4x6.4m	
FR30	2001-001195	R-CARBON(S);82ohm,5%,1/2W,AA,TP,2.4x6.4m	
FR10	2001-001195	R-CARBON(S);82ohm,5%,1/2W,AA,TP,2.4x6.4m	
RR3	2003-000554	R-METAL OXIDE(S);2.2OHM,5%,1W,AA,TP,3.3X	
JW4	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW3	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW2	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW19	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW6	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW73	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW8	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW82	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW9	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW1	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW10	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW11	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW110	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW14	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW18	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW17	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW16	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW15	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW13	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
JW12	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
HR8	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
HR7	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
DR62	2007-000241	R-CHIP;1.5KOHM,5%,1/10W,DA,TP,2012	
FR13R	2007-000267	R-CHIP;1.8KOHM,5%,1/10W,DA,TP,2012	
FR24L	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
FR12R	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
AR5	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
DR52	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
DR51	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
UR31	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR32	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR33	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR45	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
FR28L	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
FR28R	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR29	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR30	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
FR4R	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
FR4L	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
FR27R	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
FR27L	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
UR27	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
UR26	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
RR12	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
AR40	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
AR4	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
FR2R	2007-000518	R-CHIP;2.7KOHM,5%,1/10W,DA,TP,2012	
FR2L	2007-000518	R-CHIP;2.7KOHM,5%,1/10W,DA,TP,2012	
UR25	2007-000565	R-CHIP;220KOHM,5%,1/10W,DA,TP,2012	
UR28	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
FR11R	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
FR11L	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
DR64	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
DR60	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
RR8	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
DR49	2007-000653	R-CHIP;27KOHM,5%,1/10W,DA,TP,2012	
HR1	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
FR14R	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
FR14L	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
DR56	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
HR9	2007-000710	R-CHIP;3.9KOHM,5%,1/10W,DA,TP,2012	
HR10	2007-000710	R-CHIP;3.9KOHM,5%,1/10W,DA,TP,2012	
HR3	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
HR21	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
FR5L	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
DR67	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
DR63	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
UR41	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
UR42	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
UR43	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
UR44	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
UR40	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
DR65	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
HR21	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
HR5	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
HR6	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
FR7R	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
FR7L	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
UR24	2007-001024	R-CHIP;560KOHM,5%,1/10W,DA,TP,2012	

Location no.	Code no.	Description & Specifiation	Remarks
DR48	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
DR47	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
FR23	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012	
FR20	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012	
DR46	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012	
UR23	2007-001654	R-CHIP;10MOHM,1%,1/10W,DA,TP,201	
FC1R	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
FC1L	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
UC7	2201-000389	C-CERAMIC,DISC;0.022nF,5%,50V,NP0,TP,5x3	
UC6	2201-000389	C-CERAMIC,DISC;0.022nF,5%,50V,NP0,TP,5x3	
UC10	2202-000854	C-CERAMIC,MLC-AXIAL;47nF,30%,50V,Y5R,TP,	
FC9R	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
FC9L	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
FC10R	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
FC10L	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
UC8	2203-000239	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,2012	
FC14R	2203-000239	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,2012	
FC14L	2203-000239	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,2012	
DC48	2203-000239	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,2012	
DC40	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,2012,-,T	
HC5	2203-000595	C-CERAMIC,CHIP;220PF,5%,50V,NPO,TP,2012	
HC4	2203-000595	C-CERAMIC,CHIP;220PF,5%,50V,NPO,TP,2012	
FC20R	2203-000595	C-CERAMIC,CHIP;220PF,5%,50V,NPO,TP,2012	
FC20L	2203-000595	C-CERAMIC,CHIP;220PF,5%,50V,NPO,TP,2012	
HC7	2203-000787	C-CERAMIC,CHIP;330PF,0.1,50V,Y5P,2012,-,	
HC6	2203-000787	C-CERAMIC,CHIP;330PF,0.1,50V,Y5P,2012,-,	
DC47	2203-000787	C-CERAMIC,CHIP;330PF,0.1,50V,Y5P,2012,-,	
DC45	2203-000787	C-CERAMIC,CHIP;330PF,0.1,50V,Y5P,2012,-,	
CC4	2203-000892	C-CERAMIC,CHIP;4.7NF,10%,50V,X7R,TP,2012	
CC5	2203-000892	C-CERAMIC,CHIP;4.7NF,10%,50V,X7R,TP,2012	
CC6	2203-000892	C-CERAMIC,CHIP;4.7NF,10%,50V,X7R,TP,2012	
CC3	2203-000892	C-CERAMIC,CHIP;4.7NF,10%,50V,X7R,TP,2012	
CC2	2203-000892	C-CERAMIC,CHIP;4.7NF,10%,50V,X7R,TP,2012	
CC1	2203-000892	C-CERAMIC,CHIP;4.7NF,10%,50V,X7R,TP,2012	
UC9	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,2012,-,T	
DC39	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,2012,-,T	
FC8R	2203-001036	C-CERAMIC,CHIP;5.6nF,10%,50V,X7R,2012,-,	
FC8L	2203-001036	C-CERAMIC,CHIP;5.6nF,10%,50V,X7R,2012,-,	
FC15L	2203-001518	C-CERAMIC,CHIP;1.8nF,10%,50V,X7R,TP,2012	
FC15R	2203-001518	C-CERAMIC,CHIP;1.8nF,10%,50V,X7R,TP,2012	
UC4	2401-000240	C-AL;100uF,20%,10V,GP,5*11mm,5mm,TP	
UC1	2401-000240	C-AL;100uF,20%,10V,GP,5*11mm,5mm,TP	
FC30R	2401-000240	C-AL;100uF,20%,10V,GP,5*11mm,5mm,TP	
RC7	2401-000303	C-AL;100uF,20%,25V,GP,6.3*11,5MM,TP	
FC33R	2401-000303	C-AL;100uF,20%,25V,GP,6.3*11,5MM,TP	
FC33L	2401-000303	C-AL;100uF,20%,25V,GP,6.3*11,5MM,TP	
FC30L	2401-000303	C-AL;100uF,20%,25V,GP,6.3*11,5MM,TP	
AC55	2401-000303	C-AL;100uF,20%,25V,GP,6.3*11,5MM,TP	
AC49	2401-000303	C-AL;100uF,20%,25V,GP,6.3*11,5MM,TP	
DC49	2401-000357	C-AL;100UF,0.2,50V,GP,8*12,5MM,SSL	
DC36	2401-000357	C-AL;100UF,0.2,50V,GP,8*12,5MM,SSL	
RC27	2401-000438	C-AL;10uF,20%,25V,GP,5*11,5mm,TP	
FC12	2401-000438	C-AL;10uF,20%,25V,GP,5*11,5mm,TP	
RC28	2401-000588	C-AL;1uF,20%,50V,GP,3*5,2.5MM,TP	
AC26R	2401-000649	C-AL;2.2UF,50V,BP,5*11MM,5MM	
AC26L	2401-000649	C-AL;2.2UF,50V,BP,5*11MM,5MM	
AC25R	2401-000649	C-AL;2.2UF,50V,BP,5*11MM,5MM	
AC25L	2401-000649	C-AL;2.2UF,50V,BP,5*11MM,5MM	
UC3	2401-000759	C-AL;220NF,20%,50V,GP,5X11MM,5MM,TP	
RC6	2401-000795	C-AL;220uF,20%,16V,GP,8*12,5MM,TP	
RC10	2401-000795	C-AL;220uF,20%,16V,GP,8*12,5MM,TP	
RC12	2401-000830	C-AL;220uF,20%,25V,GP,8*11.5,5MM,TP	
AC30	2401-001324	C-AL;470nF,20%,50V,GP,BK,3x5,1mm	
UC5	2401-001355	C-AL;470uF,20%,10V,GP,8x11.5,5MM,TP	
HC22	2401-001465	C-AL;47uF,20%,10V,GP,5*11,5mm,TP	
FC13	2401-001511	C-AL;47uF,20%,16V,GP,6*7,5MM,TP	
HC8	2401-001511	C-AL;47uF,20%,16V,GP,6*7,5MM,TP	
HC9	2401-001511	C-AL;47uF,20%,16V,GP,6*7,5MM,TP	
AC28	2401-001538	C-AL;47uF,20%,25V,GP,5*11,5mm,TP	
HC2	2401-001889	C-AL;100nF,20%,50V,GP,5*11,5mm,TP	
HC1	2401-001889	C-AL;100nF,20%,50V,GP,5*11,5mm,TP	
FC16R	2401-001889	C-AL;100nF,20%,50V,GP,5*11,5mm,TP	
FC16L	2401-001889	C-AL;100nF,20%,50V,GP,5*11,5mm,TP	
FC11R	2401-001889	C-AL;100nF,20%,50V,GP,5*11,5mm,TP	
DC38	2401-001889	C-AL;100nF,20%,50V,GP,5*11,5mm,TP	
DC38	2401-001889	C-AL;100nF,20%,50V,GP,5*11,5mm,TP	
DC46	2401-001889	C-AL;100nF,20%,50V,GP,5*11,5mm,TP	
FC11L	2401-001889	C-AL;100nF,20%,50V,GP,5*11,5mm,TP	
DC37	2401-001895	C-AL;100uF,20%,16V,GP,TP,6.3x11,2.5	
AC43	2401-001895	C-AL;100uF,20%,16V,GP,TP,6.3x11,2.5	
AC29	2401-001912	C-AL;1uF,20%,50V,GP,BK,5x11mm,2mm	
AC27	2401-001912	C-AL;1uF,20%,50V,GP,BK,5x11mm,2mm	
FC5L	2401-001919	C-AL;2.2uF,20%,50V,-,TP,4x7mm,5	
FC5R	2401-001919	C-AL;2.2uF,20%,50V,-,TP,4x7mm,5	
FC6L	2401-001919	C-AL;2.2uF,20%,50V,-,TP,4x7mm,5	
FC6R	2401-001919	C-AL;2.2uF,20%,50V,-,TP,4x7mm,5	
FC7L	2401-001919	C-AL;2.2uF,20%,50V,-,TP,4x7mm,5	
FC7R	2401-001919	C-AL;2.2uF,20%,50V,-,TP,4x7mm,5	
UC2	2401-001919	C-AL;2.2uF,20%,50V,-,TP,4x7mm,5	
FC4R	2401-001919	C-AL;2.2uF,20%,50V,-,TP,4x7mm,5	
DC31	2401-001919	C-AL;2.2uF,20%,50V,-,TP,4x7mm,5	
FC21R	2401-001919	C-AL;2.2uF,20%,50V,-,TP,4x7mm,5	
FC2L	2401-001919	C-AL;2.2uF,20%,50V,-,TP,4x7mm,5	

Location no.	Code no.	Description & Specifiation	Remarks
FC2R	2401-001919	C-AL;2.2uF,20%,50V,-,TP,4x7mm,5	
FC4L	2401-001919	C-AL;2.2uF,20%,50V,-,TP,4x7mm,5	
FC3R	2401-001919	C-AL;2.2uF,20%,50V,-,TP,4x7mm,5	
FC3L	2401-001919	C-AL;2.2uF,20%,50V,-,TP,4x7mm,5	
DC33	2401-001954	C-AL;4.7UF,20%,50V,GP,5*11,5MM,TP	
AL4	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,	
AL3	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,	
AL2	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,	
AL1	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,	
RF7	3602-000147	FUSE-CLIP;250V,7.5A,30mohm	
RF6	3602-000147	FUSE-CLIP;250V,7.5A,30mohm	
RF3	3602-000147	FUSE-CLIP;250V,7.5A,30mohm	
RF1	3602-000147	FUSE-CLIP;250V,7.5A,30mohm	
UIC1	AH11-00058A	MASK ROM;LC8672484A-5Z61,MM-B9,48K,-,QFP	
	AH97-00900L	**ASSY-CA'DECK;-,MML7,ASSY CA'DECK**	
	3809-001279	CABLE-FLAT;30V,80C,200MM,17P,1.25MM,UL28	
	3809-001282	CABLE-FLAT;30V,80C,80MM,9P,1.25MM,UL2896	
	AH59-00137A	DECK-CASSETTE;CMAL1Z200A,MM-Z100,-,-,DC1	

**** MM-ZB9 Parts List ****

	3809-001280	CABLE-FLAT;30V,80C,250MM,17P,1.25MM,UL28	
	AH26-00161A	TRANS POWER;-,MM-B9,-,5P/10P,230V,-,-,-,	
	AH31-00029A	MOTOR FAN;C161NK10B0110,RDM6015S,0.15A,-	
	AH38-10001A	FM-WIRE;1007#22,1500MM	
	AH39-00257A	POWER CORD;Z-88,-,CP2,250V,2.5A,1830MM/1	
	AH40-00024D	TUNER;KST-MN114LS1-55,MM-ZB9,-,-,-,-	
	AH42-20001P	LOOP-ANT;TT,1000MM,18.5UH	
	AH59-00134B	REMOCON-ASSY;MAX-L65,SAMSUNG,-,-,27KEY,-	
	AH59-00138B	**DECK-MECHA ASSY;-,CD,-,-,-,-,-,-**	
	3409-001078	LEAF SWITCH;MSW-1731-CVCA	
	3809-001289	CABLE-FLAT;30V,80C,90MM,16P,1MM,UL20696	
	AH31-00030A	MOTOR DC;-,RF-300CH,86MA,-,-,1~6V,1410?	
	AH59-01006A	DECK;CMS-P73SG6,MM-Z100UH,-,19.4MM,	
	AH30-00007A	PICK UP;SOH-AA,D73SG6(U)	
	AH92-00921A	**ASSY PCB CD;G3HI-1CD,G3HI-1CD,3.5S**	
IC401	1003-001162	IC-MOTOR DRIVER;KA3082,SIP,10PIN,25MIL,D	
X201	2802-000211	RESONATOR-CERAMIC;16.93MHz,0.5%,TP,10.0x	
CW105	3708-000189	CONNECTOR-FPC/FFC/PIC;17P,1.25mm,ANGLE,S	
CW101	3708-001388	CONNECTOR-FPC/FFC/PIC;16P,1MM,ANGLE,SN	
CW103	3711-000988	CONNECTOR-HEADER;BOX,5P,1R,2mm,ANGLE,SN	
CW106	AH39-00060A	LEAD CONNECTOR-ASSY;-,51015-08,51004-08,	
ZD301	0403-000344	DIODE-ZENER;UZ3.9B,3.9V,3.7-4.1V,500mW,D	
ZD401	0403-000357	DIODE-ZENER;UZ5.6BM,5.6V,5.4-5.8V,500mW,	
Q302	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,	
Q101	0501-000314	TR-SMALL SIGNAL;KSA812,PNP,150mW,SOT-23,	
Q301	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,	
IC201	0904-001524	IC-DSP;5L9290,-,QFP,48P,472MIL,16.934	
IC301	1003-000179	IC-MOTOR DRIVER;KA9258D,SOP,28P,-,SINGLE	
IC602	1105-001339	IC-DRAM;11L1644,4Mx4Bit,TSOP24P,300MI	
IC101	1204-001799	IC-ASP;KB9226,LQFP,48P,393MIL,PLASTIC	
IC601	1204-001885	IC-DECODER;S5L9276,LQFP,64P,-,PLASTIC,3.	
R502L	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R203	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R802	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R804	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R805	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R806	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R812	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R801	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R205	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R211	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R212	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R213	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R605	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R803	2001-000515	R-CARBON;220ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R206	2001-000515	R-CARBON;220ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R302	2001-001006	R-CARBON;82ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R114	2007-000001	R-CHIP;68KOHM,5%,1/10W,DA,TP,2012	
J46	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J45	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J44	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J41	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J42	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J43	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J35	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J36	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J37	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J38	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW11	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J34	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J20	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J24	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J31	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	

Location no.	Code no.	Description & Specifiation	Remarks
J32	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J33	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
J24	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J25	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J3	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J23	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J22	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J21	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J9	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J8	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J7	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J6	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J5	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J4	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J14	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J13	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J12	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J11	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J10	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J1	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J2	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J19	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J18	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J17	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J16	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
J15	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
R501R	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
R501L	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
R502R	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
R132	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R133	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R108	2007-000308	R-CHIP;10OHM,5%,1/10W,DA,TP,2012	
R124	2007-000338	R-CHIP;120KOHM,5%,1/10W,DA,TP,2012	
R125	2007-000338	R-CHIP;120KOHM,5%,1/10W,DA,TP,2012	
R117	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
R121	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
R113	2007-000444	R-CHIP;180KOHM,5%,1/10W,DA,TP,2012	
R110	2007-000457	R-CHIP;18KOHM,5%,1/10W,DA,TP,2012	
R603	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R602	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R601	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R402	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R401	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R209	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R202	2007-000477	R-CHIP;1MOHM,5%,1/10W,DA,TP,2012	
R118	2007-000477	R-CHIP;1MOHM,5%,1/10W,DA,TP,2012	
R303	2007-000502	R-CHIP;2.2OHM,5%,1/10W,DA,TP,2012	
R303	2007-000502	R-CHIP;2.2OHM,5%,1/10W,DA,TP,2012	
R116	2007-000546	R-CHIP;20KOHM,5%,1/10W,DA,TP,2012	
R204	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
R207	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
R208	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
R604	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
R128	2007-000653	R-CHIP;27KOHM,5%,1/10W,DA,TP,2012	
R123	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
R129	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
R104	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
R120	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
R126	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
R103	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
R102	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
R101	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
R115	2007-001177	R-CHIP;8.2KOHM,5%,1/10W,DA,TP,2012	
R112	2007-001195	R-CHIP;820KOHM,5%,1/10W,DA,TP,2012	
R127	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012	
R119	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012	
R106	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012	
R105	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012	
R107	2007-001216	R-CHIP;82OHM,5%,1/10W,DA,TP,2012	
R301	2008-000140	R-FUSIBLE;2.2ohm,5%,1/2W,AA,TP,3.5x9.4mm	
C602	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C601	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C402	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C220	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C218	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C612	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C611	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C610	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C607	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C604	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C216	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C130	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C129	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C118	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C116	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C115	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C213	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C211	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C205	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C204	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C132	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
C199	2203-000239	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,2012	
C401	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,2012,-,T	

Location no.	Code no.	Description & Specifiation	Remarks
C207	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,2012,-,T	
C134	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,2012,-,T	
C121	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,2012,-,T	
C103	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,2012,-,T	
C124	2203-000347	C-CERAMIC,CHIP;150nF,10%,50V,NPO,2012,-,	
JW9<->JW10	2203-000477	C-CERAMIC,CHIP;1uF,+80-20%,16V,Y5V,2012,	
C126	2203-000495	C-CERAMIC,CHIP;2.2nF,10%,50V,X7R,2012,-,	
C127	2203-000595	C-CERAMIC,CHIP;220PF,5%,50V,NPO,TP,2012	
C105	2203-000671	C-CERAMIC,CHIP;27nF,10%,50V,X7R,2012,-,T	
C119	2203-000802	C-CERAMIC,CHIP;33NF,10%,50V,X7R,2012,TP	
C128	2203-000802	C-CERAMIC,CHIP;33NF,10%,50V,X7R,2012,TP	
C125	2203-000840	C-CERAMIC,CHIP;390pF,5%,50V,NPO,2012,-,T	
C112	2203-000892	C-CERAMIC,CHIP;4.7NF,10%,50V,X7R,TP,2012	
C111	2203-000892	C-CERAMIC,CHIP;4.7NF,10%,50V,X7R,TP,2012	
C120	2203-000919	C-CERAMIC,CHIP;470nF,+80-20%,16V,Y5V,201	
C135	2203-000919	C-CERAMIC,CHIP;470nF,+80-20%,16V,Y5V,201	
C109	2203-001026	C-CERAMIC,CHIP;4pF,5%,16V,NPO,2012,-,TP	
C124A	2203-001063	C-CERAMIC,CHIP;56nF,10%,16V,X7R,1608,-,T	
C106	2203-001137	C-CERAMIC,CHIP;68nF,+80-20%,50V,Y5V,2012	
C122	2203-001137	C-CERAMIC,CHIP;68nF,+80-20%,50V,Y5V,2012	
C608	2203-001223	C-CERAMIC,CHIP;820pF,10%,50V,X7R,2012,2.	
C605	2203-001223	C-CERAMIC,CHIP;820pF,10%,50V,X7R,2012,2.	
C203	2203-001223	C-CERAMIC,CHIP;820pF,10%,50V,X7R,2012,2.	
C502R	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
C502L	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
C117	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
C102	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
C104	2203-001551	C-CERAMIC,CHIP;1.5nF,10%,50V,X7R,TP,2012	
C202	2203-001619	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,201	
C201	2203-001619	C-CERAMIC,CHIP;0.027nF,5%,50V,NP0,TP,201	
C123	2401-000407	C-AL;10uF,20%,16V,GP,3.5*5,2.5MM,TP	
C303	2401-001102	C-AL;330uF,20%,16V,GP,8*11.5,5MM,TP	
C301	2401-001102	C-AL;330uF,20%,16V,GP,8*11.5,5MM,TP	
C501R	2401-001238	C-AL;4.7uF,20%,25V,GP,BK,3x5,1mm	
C501L	2401-001238	C-AL;4.7uF,20%,25V,GP,BK,3x5,1mm	
C114	2401-001238	C-AL;4.7uF,20%,25V,GP,BK,3x5,1mm	
C219	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C212	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C133	2401-001502	C-AL;47uF,20%,16V,GP,TP,6.3x5,2.5	
C302	2401-001893	C-AL;100uF,20%,16V,GP,TP,6.3x7,5	
C217	2401-001934	C-AL;220uF,20%,6.3V,GP,6.3x7,2.5MM	
C304	2401-001934	C-AL;220uF,20%,6.3V,GP,6.3x7,2.5MM	
C603	2401-001934	C-AL;220uF,20%,6.3V,GP,6.3x7,2.5MM	
C606	2401-001934	C-AL;220uF,20%,6.3V,GP,6.3x7,2.5MM	
R502L	2401-001934	C-AL;220uF,20%,6.3V,GP,6.3x7,2.5MM	
C215	2401-001934	C-AL;220uF,20%,6.3V,GP,6.3x7,2.5MM	
C101	2401-001934	C-AL;220uF,20%,6.3V,GP,6.3x7,2.5MM	
C107	2401-001934	C-AL;220uF,20%,6.3V,GP,6.3x7,2.5MM	
C108	2401-001934	C-AL;220uF,20%,6.3V,GP,6.3x7,2.5MM	
C131	2401-001934	C-AL;220uF,20%,6.3V,GP,6.3x7,2.5MM	
C210	2401-001934	C-AL;220uF,20%,6.3V,GP,6.3x7,2.5MM	
JW31-1	2701-000111	INDUCTOR-AXIAL;100uH,10%,2.5x3.4mm	
	AH97-00863A	**ASSY CDP DECK-G3HI-1CD/MP3;-,-,G3HI-1CD/**	
	3302-000159	MAGNET-FERRITE;AC,-,3500-3800G,6P FERRIT	
	3409-001119	SWITCH-DETECTOR;5V DC,1.0A,DPST,30gf,-	
	AH39-00104A	LEAD CONNECTOR-ASSY;-,35023,51004,5P,200	
	AH59-01038B	**SPEAKER SYSTEM;PSB9E,-,-,-,-,-,-,-,ELS,-**	
	AH92-01330D	**ASSY PCB-EXP,NO MIC,TAP;MM-B9,SUM**	
ULED1	0601-001432	LED;SLP340BL10F,470NM,3MM	
ULED2	0601-001432	LED;SLP340BL10F,470NM,3MM	
ULED5	0601-001581	LED;ROUND,BLUE/GRN/RED,5MM,-	
UVR1	3406-001047	SWITCH-ROTARY;RE012104PVB25FINB1-2-24E	
UVR2	3406-001050	SWITCH-ROTARY;RE012103PVB25FINB1-2-24PCE	
UVR3	3406-001050	SWITCH-ROTARY;RE012103PVB25FINB1-2-24PCE	
UCW5	3708-000219	CONNECTOR-FPC/FFC/PIC;21P,1.25mm,STRAIGH	
UCW2	3711-000596	CONNECTOR-HEADER;BOX,10P,1R,2mm,STRAIGHT	
UCW3	3711-000968	CONNECTOR-HEADER;BOX,4P,1R,2mm,STRAIGHT,	
HCW2	3711-001136	CONNECTOR-HEADER;BOX,8P,1R,2mm,ANGLE,SN	
ACW2	3711-003107	CONNECTOR-HEADER;BOX,3P,1R,2.5mm,STRAIGH	
HJ1	3722-001588	JACK-PHONE;7P,3.6PI,AG,BLK,-	
LCD1	AH07-00064A	LCD;-,MM-B9,8.56*40,-,-,-,-,5V,-,-	
UCW6	AH39-00393A	CONNECT WIRE;-,-,-,10P;-,-,-,5295,51004,	
UCW5	AH39-00398A	CONNECT WIRE;-,-,-,4P,-,-,-,35023,51004,	
AMONO WIRE	AH39-50001K	LEAD-FASTEN;RING,1007#24,140MM,BLK	
RMC1	AH59-60001J	MODULE REMOCON;GP1U271R,38KHZ,-,MESH,-,	
	AH61-00898A	HOLDER-LCD;MM-B9,ABS 94HB,-,-,-,WHT,-	
	AH63-00364A	FILTER-LCD;MM-B9,KIMO,120,-,-,-,-	
	AH67-00141A	LENS-LCD;MM-B9,PMMA,CLEAR,-,-,-,-	
XD4	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
XD3	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
XD2	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
XD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
UD51	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
UD52	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
UJW14	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
UQ9	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-	
UQ8	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-	
UQ5	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-	
UQ3	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-	
UQ10	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-	

Location no.	Code no.	Description & Specifiation	Remarks
UR80	2001-000027	R-CARBON;100ohm,5%,1/4W,AA,TP,2.4x6.4mm	
UR79	2001-000027	R-CARBON;100ohm,5%,1/4W,AA,TP,2.4x6.4mm	
HR2	2001-000110	R-CARBON;10ohm,5%,1/4W,AA,TP,2.4x6.4mm	
HR1	2001-000110	R-CARBON;10ohm,5%,1/4W,AA,TP,2.4x6.4mm	
UR69	2001-000221	R-CARBON;1.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR76	2001-000221	R-CARBON;1.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR75	2001-000241	R-CARBON;1.5Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR68	2001-000241	R-CARBON;1.5Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR50	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR49	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR92	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR91	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR90	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR84	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR86	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR88	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR70	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR77	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR74	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR67	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR73	2001-000472	R-CARBON;2.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR66	2001-000472	R-CARBON;2.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR65	2001-000613	R-CARBON;3.9Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR72	2001-000613	R-CARBON;3.9Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR51	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR64	2001-000802	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR71	2001-000995	R-CARBON;820ohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR78	2001-000995	R-CARBON;820ohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR59	2001-001107	R-CARBON(S);220ohm,5%,1/2W,AA,TP,2.4x6.4	
UR58	2001-001107	R-CARBON(S);220ohm,5%,1/2W,AA,TP,2.4x6.4	
UR57	2001-001107	R-CARBON(S);220ohm,5%,1/2W,AA,TP,2.4x6.4	
HC12	2202-000850	C-CERAMIC,MLC-AXIAL;2.2NF,20%,16V,Y5R	
HC11	2202-000850	C-CERAMIC,MLC-AXIAL;2.2NF,20%,16V,Y5R	
UC52	2202-000854	C-CERAMIC,MLC-AXIAL;47nF,30%,50V,Y5R,TP,	
HL2	2701-000298	INDUCTOR-AXIAL;470uH,10%,4.2x9.8mm	
HL1	2701-000298	INDUCTOR-AXIAL;470uH,10%,4.2x9.8mm	
HL3	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,	
USW5	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW4	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW3	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW2	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW6	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW7	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW8	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW9	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW17	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW1	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW10	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW11	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW12	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW16	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW15	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW14	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
USW13	3404-001182	SWITCH-TACT;DC12V,50MA,100GF,6.0X6.0X5.0	
	AH92-01331A	**ASSY PCB-TAPE;MM-B9,TAPE**	
JIC1	1201-001819	IC-PREAMP;-,-,44P,-,-,-,PLASTIC,18V,625M	
JCON2	3708-000193	CONNECTOR-FPC/FFC/PIC;17P,1.25mm,STRAIGH	
JCON3	3708-001029	CONNECTOR-FPC/FFC/PIC;9P,1.25mm,STRAIGHT	
JL1R	AH26-10002W	COIL-TRAP;BIAS-TRAP105K,BIAS-TRAP,32DB,9	
JL1L	AH26-10002W	COIL-TRAP;BIAS-TRAP105K,BIAS-TRAP,32DB,9	
JT1	AH26-10003C	COIL-TRAP;PCHNS-5371EQJ,BIAS-TRAP,-,-,85	
JCON1	AH39-00360A	LEAD CONNECTOR ASSY;MM-Z100,1533#28,-,6P	
JD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
JD2	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
JZD1	0403-000354	DIODE-ZENER;UZ5.1B,5.1V,4.8-5.4V,500mW,D	
JQ5R	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,	
JQ5L	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,	
JQ4R	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,	
JQ4L	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,	
JQ9	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1000mW,TO-	
JQ8	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
JQ7	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,	
JQ13	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,	
JQ12	0501-000610	TR-SMALL SIGNAL;KSA928A-Y,PNP,1W,TO-92L,	
JQ10	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-	
JQ11	0504-000118	TR-DIGITAL;KSR1003,NPN,300MW,22K/22K,TO-	
JQ3	0504-001003	TR-DIGITAL;KSR2003TA,300mW,22K-22Kohm	
JR18	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR19	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR28L	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR28R	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR21	2001-000034	R-CARBON;220ohm,5%,1/4W,AA,TP,2.4x6.4mm	
JR26L	2001-000241	R-CARBON;1.5Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR26R	2001-000241	R-CARBON;1.5Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR16	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR27R	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR27L	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR33	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR40	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR32R	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR32L	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR2	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	

Location no.	Code no.	Description & Specifiation	Remarks
JR1	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR7R	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR7L	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR24R	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR24L	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR14	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR35	2001-000435	R-CARBON;1Mohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR9	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR5R	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR5L	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR31R	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR30L	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR30R	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR31L	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR13	2001-000456	R-CARBON;2.2ohm,5%,1/4W,AA,TP,2.4x6.4mm	
JR8	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR34	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR3	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR11L	2001-000563	R-CARBON;27Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR11R	2001-000563	R-CARBON;27Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR10	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR17	2001-000660	R-CARBON;33Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR20	2001-000660	R-CARBON;33Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR4R	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR4L	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR41	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR39	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR38	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR37	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR36	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
JR29R	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR29L	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR25R	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR25L	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
JR12	2001-001153	R-CARBON(S);47ohm,5%,1/2W,AA,TP,2.4x6.4m	
JR23	2001-001178	R-CARBON(S);680ohm,5%,1/2W,AA,TP,2.4x6.4	
JR22	2001-001178	R-CARBON(S);680ohm,5%,1/2W,AA,TP,2.4x6.4	
JC19R	2201-000163	C-CERAMIC,DISC;10nF,+80-20%,50V,Y5V,6.5*	
JC19L	2201-000163	C-CERAMIC,DISC;10nF,+80-20%,50V,Y5V,6.5*	
JC17R	2201-000163	C-CERAMIC,DISC;10nF,+80-20%,50V,Y5V,6.5*	
JC17L	2201-000163	C-CERAMIC,DISC;10nF,+80-20%,50V,Y5V,6.5*	
JC4R	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
JC4L	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
JC15R	2201-000783	C-CERAMIC,DISC;100nF,+80-20%,50V,Y5V,TP,	
JC15L	2201-000783	C-CERAMIC,DISC;100nF,+80-20%,50V,Y5V,TP,	
JC11L	2202-000847	C-CERAMIC,MLC-AXIAL;1,8nF,30%,50V,Y5S,TP	
JC11R	2202-000847	C-CERAMIC,MLC-AXIAL;1,8nF,30%,50V,Y5S,TP	
JC22R	2202-000850	C-CERAMIC,MLC-AXIAL;2.2NF,20%,16V,Y5R	
JC22L	2202-000850	C-CERAMIC,MLC-AXIAL;2.2NF,20%,16V,Y5R	
JC13L	2301-000379	C-FILM,PEF;10nF,10%,50V,6x12x3.5,TP	
JC13R	2301-000379	C-FILM,PEF;10nF,10%,50V,6x12x3.5,TP	
JC8	2301-000390	C-FILM,PEF;15nF,10%,50V,7x12x3.5,TP	
JC6	2301-000404	C-FILM,PEF;2.2nF,10%,50V,5.5x12x3,TP	
JC5	2301-000407	C-FILM,PEF;2.7nF,10%,50V,5.5x12x3,TP	
JC27	2401-000240	C-AL;100uF,20%,10V,GP,5*11mm,5mm,TP	
JC24	2401-000303	C-AL;100uF,20%,25V,GP,6.3*11,5MM,TP	
JC30	2401-001912	C-AL;1uF,20%,50V,GP,BK,5x11mm,2mm	
JC18R	2401-001912	C-AL;1uF,20%,50V,GP,BK,5x11mm,2mm	
JC18L	2401-001912	C-AL;1uF,20%,50V,GP,BK,5x11mm,2mm	
JC10	2401-001912	C-AL;1uF,20%,50V,GP,BK,5x11mm,2mm	
JC3	2401-001954	C-AL;4.7UF,20%,50V,GP,5*11,5MM,TP	
JC23	2401-001954	C-AL;4.7UF,20%,50V,GP,5*11,5MM,TP	
JC16R	2401-001954	C-AL;4.7UF,20%,50V,GP,5*11,5MM,TP	
JC16L	2401-001954	C-AL;4.7UF,20%,50V,GP,5*11,5MM,TP	
JC9R	2401-001975	C-AL;47uF,20%,16V,GP,5*11,5mm,TP	
JC9L	2401-001975	C-AL;47uF,20%,16V,GP,5*11,5mm,TP	
JC7	2401-001975	C-AL;47uF,20%,16V,GP,5*11,5mm,TP	
JC20R	2401-002180	C-AL;2.2uF,20%,50V,GP,5*11,5mm,TP	
JC20L	2401-002180	C-AL;2.2uF,20%,50V,GP,5*11,5mm,TP	
JL2	2701-000298	INDUCTOR-AXIAL;470uH,10%,4.2x9.8mm	
	AH92-01332A	**ASSY PCB-MAIN/POWER;MM-B9,MAIN/POWER**	
RD19	0402-000157	DIODE-RECTIFIER;1N5402,200V,3A,DO-201AD,	
RD18	0402-000157	DIODE-RECTIFIER;1N5402,200V,3A,DO-201AD,	
RD17	0402-000157	DIODE-RECTIFIER;1N5402,200V,3A,DO-201AD,	
RD16	0402-000157	DIODE-RECTIFIER;1N5402,200V,3A,DO-201AD,	
RD15	0402-000157	DIODE-RECTIFIER;1N5402,200V,3A,DO-201AD,	
RD14	0402-000157	DIODE-RECTIFIER;1N5402,200V,3A,DO-201AD,	
AQ15	0502-001126	TR-POWER;2SD2390,NPN,100W,SC-62,BK,6500	
RQ2	0502-001197	TR-POWER;KSD1406,NPN,25000MW,TO-220F	
RQ4	0502-001197	TR-POWER;KSD1406,NPN,25000MW,TO-220F	
AIC1	1201-001818	IC-POWER AMP;-,-,25P,29MIL,QUAD,26DB,PLA	
AIC4	1203-000110	IC-NEGA.FIXED REG.;7912,TO-220,3P,-,PLAS	
AIC3	1203-000242	IC-POSI.FIXED REG.;7812,TO-220,3P,-,PLAS	
RIC1	1203-000276	IC-POSI.FIXED REG.;7805,TO-220,3P,-,PLAS	
DIC7	1204-001454	IC-VOLUME CONTROL;TDA7449L,DIP,20P,300MI	
AR50	2003-000616	R-METAL OXIDE(S);27ohm,5%,2W,AA,TP,4x12m	
AR52	2003-000701	R-METAL OXIDE(S);470ohm,5%,2W,AA,TP,4x12	
RC1	2201-000546	C-CERAMIC,DISC;4.7nF,20%,400V,Y5U,16.0*7	
RC2	2201-000546	C-CERAMIC,DISC;4.7nF,20%,400V,Y5U,16.0*7	
RC9	2401-001052	C-AL;3300uF,20%,25V,GP,-,16x31.5,7.	
RC5	2401-001052	C-AL;3300uF,20%,25V,GP,-,16x31.5,7.	
RC25	2401-001413	C-AL;470UF,20%,35V,GP,10X20,5MM	

Location no.	Code no.	Description & Specifiation	Remarks
HR11<->GND	2401-001465	C-AL;47uF,20%,10V,GP,5*11,5mm,TP	
AC44	2401-001633	C-AL;6800uF,20%,25V,GP,BK,18x35.5,7	
RC26	2401-001883	C-AL;1000uF,20%,25V,GP,13x21mm,5mm,	
RC31	2401-001886	C-AL;1000uF,20%,35V,GP,16x25mm,5mm,	
RC30	2401-001886	C-AL;1000uF,20%,35V,GP,16x25mm,5mm,	
AC47	2401-001886	C-AL;1000uF,20%,35V,GP,16x25mm,5mm,	
AC46	2401-001886	C-AL;1000uF,20%,35V,GP,16x25mm,5mm,	
UX1	2801-001394	CRYSTAL-UNIT;32.768KHz,20ppm,28-AAY,12.5	
UX2	2802-001157	RESONATOR-CERAMIC;6MHZ,-,BK,8X5.5X3MM	
RRL1	3501-001159	RELAY-MINIATURE;SDT-SS-112DM	
RF1	3601-000162	FUSE-CARTRIDGE;250V,1.25A,TIME-LAG,GLASS	
RF6	3601-000170	FUSE-CARTRIDGE;250V,1.6A,TIME-LAG,GLASS,	
RF7	3601-000248	FUSE-CARTRIDGE;250V,2A,TIME-LAG,GLASS,5x	
RF3	3601-000319	FUSE;80MA(15.5MM)	
CCW3	3708-000193	CONNECTOR-FPC/FFC/PIC;17P,1.25mm,STRAIGH	
JCW1	3708-000193	CONNECTOR-FPC/FFC/PIC;17P,1.25mm,STRAIGH	
UCW1	3708-000219	CONNECTOR-FPC/FFC/PIC;21P,1.25mm,STRAIGH	
TCW1	3708-001463	CONNECTOR-FPC/FFC/PIC;11P,1.25mm,STRAIGH	
RJ1	3711-000190	CONNECTOR-HEADER;1WALL,2P,1R,7.92mm,STRA	
RCW2	3711-000658	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,STRAIG	
FA4	3711-000820	CONNECTOR-HEADER;BOX,2P,1R,2.5mm,STRAIGH	
JW	3711-000907	CONNECTOR-HEADER;BOX,3P,1R,2mm,STRAIGHT,	
RCW1	3711-001018	CONNECTOR-HEADER;BOX,5P,1R,2mm,STRAIGHT,	
CCW2	3711-001137	CONNECTOR-HEADER;BOX,8P,1R,2mm,STRAIGHT,	
AJ1	3716-001132	TERMINAL-BLOCK;SOLDER,4P,-,-,-	
AJ2	3716-001179	TERMINAL-BLOCK;SOLDER,4P,6.3MM,60V,7A	
AJ4	3722-000377	JACK-RCA;4P/2C,3.5mm,#16~22,SN	
RT2	AH26-00161C	TRANS POWER;-,MM-B9,-,-,230V,8.7V,15.5V,	
RL1	AH27-10001F	COIL-CHOKE;27uH,K,Q30,-,-,DR(6.5*7.5),-,	
RL2	AH27-10001F	COIL-CHOKE;27uH,K,Q30,-,-,DR(6.5*7.5),-,	
HCW1	AH39-00103A	LEAD CONNECTOR-ASS;-,5295,51004,8P,210MM	
FAW1<->FAW1-1	AH39-00307A	WIRE HARNESS;MM-L7,-,-,2P;-,-,-,5295,529	
PCW1	AH39-00399A	CONNECT WIRE;-,-,-,12P,-,-,-,5264,51088,	
	AH39-00400A	CONNECT WIRE;-,-,-,3P,-,-,-,5264,51088,-	
CCW1	AH39-20006G	LEAD-CONNECTOR ASS'Y;51004,5295,5P,300MM	
B	AH39-50001K	LEAD-FASTEN;RING,1007#24,140MM,BLK	
	AH62-00067A	INSULATION-RUBBER;MM-B9,TC-20CG,-,-,-,PI	
UD6	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
UD7	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
UD8	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
UD9	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
AD1	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
RD36	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
UD10	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
UD12	0401-000101	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
RD41	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD40	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD4	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD39	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD37	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD8	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD7	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD6	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD5	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD44	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD13	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD12	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD11	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD10	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD1	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD35	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD33	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD32	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD3	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RD2	0402-000127	DIODE-RECTIFIER;1N4002,100V,1A,DO-41,TP	
RZD8	0403-000354	DIODE-ZENER;UZ5.1B,5.1V,4.8-5.4V,500mW,D	
RZD1	0403-000379	DIODE-ZENER;UZP12B,12V,11.4-12.6V,1W,DO-	
AZD1	0403-000379	DIODE-ZENER;UZP12B,12V,11.4-12.6V,1W,DO-	
AZD2	0403-000393	DIODE-ZENER;UZP5.1B,5.1V,4.8-5.4V,1W,DO-	
RZD3	0403-000399	DIODE-ZENER;UZP9.1B,8.5-9.6V,1W,DO-41,TP	
FZD2	0403-000399	DIODE-ZENER;UZP9.1B,8.5-9.6V,1W,DO-41,TP	
FZD1	0403-000399	DIODE-ZENER;UZP9.1B,8.5-9.6V,1W,DO-41,TP	
AQ13	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,	
RQ16	0501-000010	TR-SMALL SIGNAL;KSC1008,NPN,800mW,TO-92,	
RQ5	0501-000294	TR-SMALL SIGNAL;KSA708-Y,PNP,800mW,TO-92	
UQ1	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
RQ6	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
HQ2	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
HQ1	0501-000398	TR-SMALL SIGNAL;KSC945,NPN,250mW,TO-92,T	
FQ2	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9	
FQ1	0501-000407	TR-SMALL SIGNAL;KSD471A-Y,NPN,800mW,TO-9	
HQ3	0504-001003	TR-DIGITAL;KSR2003TA,300mW,22K-22Kohm	
FQ3	0504-001003	TR-DIGITAL;KSR2003TA,300mW,22K-22Kohm	
HIC1	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/m	
FIC5	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/m	
FIC3	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/m	
FIC2	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/m	
DIC9	1201-000163	IC-OP AMP;4560,SOP,8P,173MIL,DUAL,100V/m	
FIC1	1204-001776	IC-SOUND PROCESSOR;TDA7442D,SOP,28P,295M	
FR5R	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR5L/1	2001-000008	R-CARBON;15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR31	2001-000019	R-CARBON(S);10ohm,5%,1/2W,AA,TP,2.4x6.4m	
RR10	2001-000027	R-CARBON;100ohm,5%,1/4W,AA,TP,2.4x6.4mm	

Location no.	Code no.	Description & Specifiation	Remarks
RR11	2001-000027	R-CARBON;100ohm,5%,1/4W,AA,TP,2.4x6.4mm	
FR13L	2001-000258	R-CARBON;1.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR12L	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR24R	2001-000273	R-CARBON;100Kohm,5%,1/8W,AA,TP,1.8x3.2m	
UR2	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR1	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR54	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR53	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR30	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
RR13	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR26R	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR26L	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
AR36	2001-000290	R-CARBON;10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DR61	2001-000331	R-CARBON;12Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR6L	2001-000411	R-CARBON;18Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR6R	2001-000411	R-CARBON;18Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR14	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR15	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR17	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR8	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR9	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR13	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
RR35	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
RR39	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR10	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR11	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
UR12	2001-000429	R-CARBON;1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR25R	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR25L	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
AR13R	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
AR13L	2001-000449	R-CARBON;2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
RR9	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR3R	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
FR3L	2001-000522	R-CARBON;22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
HR4	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
HR11	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR1R	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR1L	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
RR38	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
RR37	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
FR5L	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
AR19	2001-000786	R-CARBON;47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
AR12L	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
AR12R	2001-000864	R-CARBON;56Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
RR36	2001-000890	R-CARBON;6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
AR51	2001-001077	R-CARBON(S);150ohm,5%,1/2W,AA,TP,2.4x6.4	
RR4	2001-001107	R-CARBON(S);220ohm,5%,1/2W,AA,TP,2.4x6.4	
RR101	2001-001195	R-CARBON(S);82ohm,5%,1/2W,AA,TP,2.4x6.4m	
FR30	2001-001195	R-CARBON(S);82ohm,5%,1/2W,AA,TP,2.4x6.4m	
FR10	2001-001195	R-CARBON(S);82ohm,5%,1/2W,AA,TP,2.4x6.4m	
RR3	2003-000554	R-METAL OXIDE(S);2.2OHM,5%,1W,AA,TP,3.3X	
RR100	2003-000708	R-METAL OXIDE(S);47OHM,5%,1W,AA,TP	
JW4	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW3	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW2	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW19	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW6	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW73	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW8	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW82	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW9	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW1	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW10	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW11	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW110	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW14	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW18	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW17	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW16	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW15	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
JW13	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
JW12	2007-000033	R-CHIP;0OHM,5%,1/8W,DA,TP,3216	
HR8	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
HR7	2007-000221	R-CHIP;1.2KOHM,5%,1/10W,DA,TP,2012	
DR62	2007-000241	R-CHIP;1.5KOHM,5%,1/10W,DA,TP,2012	
FR13R	2007-000267	R-CHIP;1.8KOHM,5%,1/10W,DA,TP,2012	
FR24L	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
FR12R	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
AR5	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012	
DR52	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
DR51	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
UR31	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR32	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR33	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR45	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
FR28L	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
FR28R	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR29	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
UR30	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
FR4R	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
FR4L	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
FR27R	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
FR27L	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	

Location no.	Code no.	Description & Specifiation	Remarks
UR27	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
UR26	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
RR12	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
AR40	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
AR4	2007-000493	R-CHIP;2.2KOHM,5%,1/10W,DA,TP,2012	
FR2R	2007-000518	R-CHIP;2.7KOHM,5%,1/10W,DA,TP,2012	
FR2L	2007-000518	R-CHIP;2.7KOHM,5%,1/10W,DA,TP,2012	
UR25	2007-000565	R-CHIP;220KOHM,5%,1/10W,DA,TP,2012	
DR50	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
UR28	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
FR11R	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
FR11L	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
DR64	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
DR60	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
RR8	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
DR49	2007-000653	R-CHIP;27KOHM,5%,1/10W,DA,TP,2012	
HR1	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
FR14R	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
FR14L	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
DR56	2007-000686	R-CHIP;3.3KOHM,5%,1/10W,DA,TP,2012	
HR3	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
HR21	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
FR5L	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
DR67	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
DR63	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012	
UR41	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
UR42	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
UR43	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
UR44	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
UR40	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
DR65	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
HR21	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
HR5	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
HR6	2007-000941	R-CHIP;47KOHM,5%,1/10W,DA,TP,2012	
HR9	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
HR10	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
FR7R	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
FR7L	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
UR23	2007-001024	R-CHIP;560KOHM,5%,1/10W,DA,TP,2012	
DR48	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
DR47	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
DR46	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012	
FR20	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012	
FR23	2007-001208	R-CHIP;82KOHM,5%,1/10W,DA,TP,2012	
UR24	2007-001654	R-CHIP;10MOHM,1%,1/10W,DA,TP,201	
RC8	2201-000161	C-CERAMIC,DISC;10nF,+80-20%,500V,Y5V,10x	
RC4	2201-000161	C-CERAMIC,DISC;10nF,+80-20%,500V,Y5V,10x	
RC13	2201-000161	C-CERAMIC,DISC;10nF,+80-20%,500V,Y5V,10x	
FC1L	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
FC1R	2201-000368	C-CERAMIC,DISC;220pF,10%,50V,SL,TP,6.5x3	
UC7	2201-000389	C-CERAMIC,DISC;0.022nF,5%,50V,NP0,TP,5x3	
UC6	2201-000389	C-CERAMIC,DISC;0.022nF,5%,50V,NP0,TP,5x3	
UC10	2201-000565	C-CERAMIC,DISC;47nF,+80% -20% 50V Y5V 12	
FC50	2202-000807	C-CERAMIC,MLC-AXIAL;22nF,+80-20%,25V,Y5V	
FC9R	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
FC9L	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
FC10R	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
FC10L	2203-000203	C-CERAMIC,CHIP;100nF,10%,16V,X7R,TP,2012	
UC8	2203-000239	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,2012	
FC14R	2203-000239	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,2012	
FC14L	2203-000239	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,2012	
DC48	2203-000239	C-CERAMIC,CHIP;0.1nF,5%,50V,NP0,TP,2012	
DC40	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,2012,-,T	
HC5	2203-000595	C-CERAMIC,CHIP;220PF,5%,50V,NPO,TP,2012	
HC4	2203-000595	C-CERAMIC,CHIP;220PF,5%,50V,NPO,TP,2012	
FC20R	2203-000595	C-CERAMIC,CHIP;220PF,5%,50V,NPO,TP,2012	
FC20L	2203-000595	C-CERAMIC,CHIP;220PF,5%,50V,NPO,TP,2012	
HC7	2203-000787	C-CERAMIC,CHIP;330PF,0.1,50V,Y5P,2012,-,	
HC6	2203-000787	C-CERAMIC,CHIP;330PF,0.1,50V,Y5P,2012,-,	
DC47	2203-000787	C-CERAMIC,CHIP;330PF,0.1,50V,Y5P,2012,-,	
DC45	2203-000787	C-CERAMIC,CHIP;330PF,0.1,50V,Y5P,2012,-,	
UC9	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,2012,-,T	
DC39	2203-000979	C-CERAMIC,CHIP;47nF,10%,50V,X7R,2012,-,T	
FC8L	2203-001036	C-CERAMIC,CHIP;5.6nF,10%,50V,X7R,2012,-,	
FC8R	2203-001036	C-CERAMIC,CHIP;5.6nF,10%,50V,X7R,2012,-,	
FC15R	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
FC15L	2203-001537	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012	
UC4	2401-000240	C-AL;100uF,20%,10V,GP,5*11mm,5mm,TP	
UC1	2401-000240	C-AL;100uF,20%,10V,GP,5*11mm,5mm,TP	
RC7	2401-000303	C-AL;100uF,20%,25V,GP,6.3*11,5MM,TP	
HC9/1	2401-000303	C-AL;100uF,20%,25V,GP,6.3*11,5MM,TP	
FC33R	2401-000303	C-AL;100uF,20%,25V,GP,6.3*11,5MM,TP	
AC49	2401-000303	C-AL;100uF,20%,25V,GP,6.3*11,5MM,TP	
FC30L	2401-000303	C-AL;100uF,20%,25V,GP,6.3*11,5MM,TP	
FC33L	2401-000303	C-AL;100uF,20%,25V,GP,6.3*11,5MM,TP	
FC30R	2401-000357	C-AL;100UF,0.2,50V,GP,8*12,5MM,SSL	
DC49	2401-000419	C-AL;10UF,20%,16V,GP,5*11,5MM,TP	
DC36	2401-000419	C-AL;10UF,20%,16V,GP,5*11,5MM,TP	
RC27	2401-000438	C-AL;10uF,20%,25V,GP,5*11,5mm,TP	
FC12	2401-000438	C-AL;10uF,20%,25V,GP,5*11,5mm,TP	
AC26R	2401-000649	C-AL;2.2UF,50V,BP,5*11MM,5MM	
AC26L	2401-000649	C-AL;2.2UF,50V,BP,5*11MM,5MM	
AC25R	2401-000649	C-AL;2.2UF,50V,BP,5*11MM,5MM	

Location no.	Code no.	Description & Specifiation	Remarks
AC25L	2401-000649	C-AL;2.2UF,50V,BP,5*11MM,5MM	
UC3	2401-000759	C-AL;220NF,20%,50V,GP,5X11MM,5MM,TP	
RC10	2401-000795	C-AL;220uF,20%,16V,GP,8*12,5MM,TP	
RC12	2401-000830	C-AL;220uF,20%,25V,GP,8*11.5,5MM,TP	
RC6	2401-000830	C-AL;220uF,20%,25V,GP,8*11.5,5MM,TP	
UC5	2401-001355	C-AL;470uF,20%,10V,GP,8x11.5,5MM,TP	
HC22	2401-001465	C-AL;47uF,20%,10V,GP,5*11,5mm,TP	
AC28	2401-001538	C-AL;47uF,20%,25V,GP,5*11,5mm,TP	
HC2	2401-001889	C-AL;100nF,20%,50V,GP,5*11,5mm,TP	
HC1	2401-001889	C-AL;100nF,20%,50V,GP,5*11,5mm,TP	
FC16R	2401-001889	C-AL;100nF,20%,50V,GP,5*11,5mm,TP	
FC16L	2401-001889	C-AL;100nF,20%,50V,GP,5*11,5mm,TP	
FC11R	2401-001889	C-AL;100nF,20%,50V,GP,5*11,5mm,TP	
DC38	2401-001889	C-AL;100nF,20%,50V,GP,5*11,5mm,TP	
DC38	2401-001889	C-AL;100nF,20%,50V,GP,5*11,5mm,TP	
DC46	2401-001889	C-AL;100nF,20%,50V,GP,5*11,5mm,TP	
FC11L	2401-001889	C-AL;100nF,20%,50V,GP,5*11,5mm,TP	
DC37	2401-001895	C-AL;100uF,20%,16V,GP,TP,6.3x11,2.5	
AC43	2401-001895	C-AL;100uF,20%,16V,GP,TP,6.3x11,2.5	
RC28	2401-001912	C-AL;1uF,20%,50V,GP,BK,5x11mm,2mm	
AC29	2401-001912	C-AL;1uF,20%,50V,GP,BK,5x11mm,2mm	
AC27	2401-001912	C-AL;1uF,20%,50V,GP,BK,5x11mm,2mm	
DC33	2401-001954	C-AL;4.7UF,20%,50V,GP,5*11,5MM,TP	
AC30	2401-001968	C-AL;470nF,20%,50V,GP,5*11,5mm,TP	
HC9	2401-001975	C-AL;47uF,20%,16V,GP,5*11,5mm,TP	
HC8	2401-001975	C-AL;47uF,20%,16V,GP,5*11,5mm,TP	
FC13	2401-001975	C-AL;47uF,20%,16V,GP,5*11,5mm,TP	
FC6L	2401-002180	C-AL;2.2uF,20%,50V,GP,5*11,5mm,TP	
FC5R	2401-002180	C-AL;2.2uF,20%,50V,GP,5*11,5mm,TP	
FC5L	2401-002180	C-AL;2.2uF,20%,50V,GP,5*11,5mm,TP	
FC4R	2401-002180	C-AL;2.2uF,20%,50V,GP,5*11,5mm,TP	
FC6R	2401-002180	C-AL;2.2uF,20%,50V,GP,5*11,5mm,TP	
FC7L	2401-002180	C-AL;2.2uF,20%,50V,GP,5*11,5mm,TP	
FC7R	2401-002180	C-AL;2.2uF,20%,50V,GP,5*11,5mm,TP	
UC2	2401-002180	C-AL;2.2uF,20%,50V,GP,5*11,5mm,TP	
DC31	2401-002180	C-AL;2.2uF,20%,50V,GP,5*11,5mm,TP	
FC21R	2401-002180	C-AL;2.2uF,20%,50V,GP,5*11,5mm,TP	
FC21R/1	2401-002180	C-AL;2.2uF,20%,50V,GP,5*11,5mm,TP	
FC2L	2401-002180	C-AL;2.2uF,20%,50V,GP,5*11,5mm,TP	
FC4L	2401-002180	C-AL;2.2uF,20%,50V,GP,5*11,5mm,TP	
FC3R	2401-002180	C-AL;2.2uF,20%,50V,GP,5*11,5mm,TP	
FC3L	2401-002180	C-AL;2.2uF,20%,50V,GP,5*11,5mm,TP	
FC2R	2401-002180	C-AL;2.2uF,20%,50V,GP,5*11,5mm,TP	
AL4	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,	
AL3	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,	
AL2	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,	
AL1	3301-000297	CORE-FERRITE BEAD;AA,3.6x1.2x5.7mm,1400,	
RF7	3602-000147	FUSE-CLIP;250V,7.5A,30mohm	
RF6	3602-000147	FUSE-CLIP;250V,7.5A,30mohm	
RF3	3602-000147	FUSE-CLIP;250V,7.5A,30mohm	
RF1	3602-000147	FUSE-CLIP;250V,7.5A,30mohm	
UIC1	AH11-00058A	MASK ROM;LC867248A-5Z61,MM-B9,48K,-,QFP	

Location no.	Code no.	Description & Specifiation	Remarks